

SHUNTS

FIGURE 6
150A—200A



FIGURE 1
5A—10A



FIGURE 2
15A—30A



FIGURE 7
250A—350A



FIGURE 3
40A—50A



FIGURE 10
600A



FIGURE 15
2500A



FIGURE 5
120A—150A



Current Automation

POWER SOLUTION PROVIDERS

www.rectifier.co.za

PHONE: 0811 400-4200 FAX: 0811 400-4210 E-MAIL: usa@rectifier.co.za

Current	Dwg	Dimensions (mm)						
		a	b	c	d1	d	e	f
50mV								
5A	Fig 1	105	85	*	*	12	6	6.5
10A	Fig 1	105	85	*	*	12	6	6.5
15A	Fig 2	105	85	*	*	12	6	6.5
20A	Fig 2	105	85	*	*	12	6	6.5
25A	Fig 2	105	85	*	*	12	6	6.5
30A	Fig 2	105	85	*	*	12	6	6.5
40A	Fig 3	105	85	*	*	19	6	6.5
50A	Fig 3	105	85	*	*	19	6	6.5
60A	Fig 4	105	85	*	*	19	9	8.5
75A	Fig 4	105	85	*	*	19	9	8.5
80A	Fig 4	105	85	*	*	19	9	8.5
100A	Fig 4	105	85	*	*	19	9	8.5
120A	Fig 5	105	85	*	*	25	10	8.5
130A	Fig 5	105	85	*	*	25	10	8.5
140A	Fig 5	105	85	*	*	25	10	8.5
150A	Fig 5	105	85	*	*	25	10	8.5
160A	Fig 6	105	85	*	*	25	12	8.5
175A	Fig 6	105	85	*	*	25	12	8.5
200A	Fig 6	105	85	*	*	25	12	8.5
250A	Fig 7	137	107	*	*	25	12	10.5
300A	Fig 7	137	107	*	*	36	12	10.5
350A	Fig 7	137	107	*	*	36	12	10.5
400A	Fig 8	137	107	*	31	36	31	10.5
450A	Fig 8	137	107	*	31	36	31	10.5
500A	Fig 9	137	107	*	31	36	31	10.5
600A	Fig 10	137	107	*	31	36	31	10.5
700A	Fig 11	137	107	32	32	56	31	10.5
750A	Fig 11	137	107	32	32	56	31	10.5
800A	Fig 12	137	107	32	32	56	31	10.5
1000A	Fig 13	137	107	32	32	56	31	10.5
1200A	Fig 14	205	115/175	55	45	75	20	12.5
1500A	Fig 14	205	115/175	55	45	75	20	12.5
1800A	Fig 14	205	115/175	55	45	75	20	12.5
2000A	Fig 14	205	115/175	55	45	75	20	12.5
2500A	Fig 15	210	120/180	75	25/25	75	20	12.5

